

Default System Short Code List

Most IP Office control units are available in A-Law and MU-Law models. Typically MU-Law models are supplied to North American locales, A-Law models are supplied to the rest of the world. In addition to the using different default companding for digital lines and phone, A-Law and MU-Law models support different default short codes.

The following table lists the default system short codes present in an IP Office Release 5+ system's configuration.

Short Code	Telephone Number	Feature	A-Law	MU-Law
*00	Blank	Cancel All Forwarding	✓	✓
*01	Blank	Forward Unconditional On	✓	✓
*02	Blank	Forward Unconditional Off	✓	✓
*03	Blank	Forward On Busy On	✓	✓
*04	Blank	Forward On Busy Off	✓	✓
*05	Blank	Forward On No Answer On	✓	✓
*06	Blank	Forward On No Answer Off	✓	✓
*07*N#	N	Forward Number	✓	✓
*08	Blank	Do Not Disturb On	✓	✓
*09	Blank	Do Not Disturb Off	✓	✓
*10*N#	N	Do Not Disturb Exception Add	✓	✓
*11*N#	N	Do Not Disturb Exception Del	✓	✓
*12*N#	N	Follow Me Here	✓	✓
*13*N#	N	Follow Me Here Cancel	✓	✓
*14*N#	N	Follow Me To	✓	✓
*15	Blank	Call Waiting On	✓	✓
*16	Blank	Call Waiting Off	✓	✓
*17	?U	Voicemail Collect	✓	✓
*18	Blank	Voicemail On	✓	✓
*19	Blank	Voicemail Off	✓	✓
*20*N#	N	Set Hunt Group Night Service	✓	✓
*21*N#	N	Clear Hunt Group Night Service	✓	✓
*22*N#	N	Suspend Call	✓	✗
*23*N#	N	Resume Call	✓	✗
*24*N#	N	Hold Call	✓	✗
*25*N#	N	Retrieve Call	✓	✗
*26		Clear CW	✓	✗
*27*N#	N	Hold CW	✓	✗
*28*N#	N	Suspend CW	✓	✗
*29	Blank	Toggle Calls	✓	✓
*30	Blank	Call Pickup Any	✓	✓
*31	Blank	Call Pickup Group	✓	✓
*32*N#	N	Call Pickup Extn	✓	✓
*33*N#	N	Call Queue	✓	✓
*34N;	N	Hold Music	✓	✓
*35*N#	N	Extn Login	✓	✓
*36	Blank	Extn Logout	✓	✓
*37*N#	N	Park Call	✓	✓
*38*N#	N	Unpark Call	✓	✓
*39	1	Relay On	✓	✓
*40	1	Relay Off	✓	✓
*41	1	Relay Pulse	✓	✓
*42	2	Relay On	✓	✓

*43	2	Relay Off	✓	✓
*44	2	Relay Pulse	✓	✓
*45*N#	N	Acquire Call	✓	✓
*46	Blank	Acquire Call	✓	✓
*47	Blank	Conference Add	✓	✓
*48	Blank	Voicemail Ringback On	✓	✓
*49	Blank	Voicemail Ringback Off	✓	✓
*50	Blank	Forward Huntgroup On	✓	✓
*51	Blank	Forward Huntgroup Off	✓	✓
*52	Blank	Cancel or Deny	✓	✓
*53*N#	N	Call Pickup Members	✓	✓
*57*N#	N	Forward On Busy Number	✓	✓
*70	Blank	Call Waiting Suspend	✓	✗
*70*N#	N	Dial Physical Extn By Number	✗	✓
*71*N#	N	Dial Physical Extn By ID	✗	✓
9000	"MAINTENANCE"	Relay On	✓	✓
*91N;	N".1"	Record Message	✓	✓
*92N;	N".2"	Record Message	✓	✓
9N	N	Dial	✗	✓
?	.	Dial	✓	✗

Additional short codes of the form *DSSN, *SDN, *SKN, these are used by the IP Office system for internal functions and should not be removed or altered. Short codes *#N and **N may also be visible, these are used for ISDN functions in Scandinavian locales.

For IP Office 4.2+, the default ***34** short code for music on hold has changed to ***34N;**.

Default auto attendant short codes of the form ***81XX**, ***82XX**, ***83XX** and ***84XX** are only added when an [Embedded Voicemail auto attendant](#) is added to the IP Office's configuration.

© 2010 AVAYA
15-601011 Issue 24.h.-
09:25, 20 February 2010
(short_codes_defaults\systemshortcodelist.htm)

Performance figures, data and operation quoted in this document are typical and must be specifically confirmed in writing by Avaya before they become applicable to any particular order or contract. The company reserves the right to make alterations or amendments at its own discretion. The publication of information in this document does not imply freedom from patent or any other protective rights of Avaya or others.

All trademarks identified by (R) or TM are registered trademarks or trademarks respectively of Avaya Inc. All other trademarks are the property of their respective owners.

http://marketingtools.avaya.com/knowledgebase/businesspartner/ipoffice/mergedProjects/manager/short_codes_defaults\systemshortcodelist.htm
Last Modified: 05/11/2009